


# Motion Sensor for Linear & Round Highbay

## HL-ANT-6-4R



HL-ANT-6-4R



### DEFAULT SETTINGS

Brightness - 100%
Sensitivity - 100%
Hold time - 30 Min

## INTRODUCTION

The HL-ANT-6-4R mounts in a Highbay lighting fixture and provides multi-level control based on motion.

It controls 0-10 VDC LED drivers or dimming ballasts, and is rated for wet and cold locations. All control parameters are adjustable via a wireless configuration tool capable of storing.

## SPECIFICATIONS

Power supply	12V-24V DC, >30mA
Dim control output	0-10V, max. 25mA sinking current
Remote range	50ft. (15m) indoor, no backlight
Detection radius	20%/50%/75%/100% (1-8m)
Mounting height	Max 40ft. (12meters)
Time setting	10s/1min/5min/10min/15min/20min/30min/60min
Light-control	24H/10LUX/30LUX/50LUX
Temperature	-4°F ~ +140°F (-20°C ~ +60°C)
IP rating	IP65

**NOTE : STANDARD MODEL IS ON/OFF TYPE. DIMMABLE SENSOR OPTION AVAILABLE UPON SPECIAL REQUEST.**

## ⚠ WARNING

**NOTE:** Warm up time is 40seconds. After the sensor connects input power first time, the light will keep on 40seconds, then go to dimming to work normally.

**NOTE:** Factory Default Setting: 100% sensitivity, Hold on time: 30min,

## SENSOR COVERAGE

