



Article No : _____
 Version : 08.25
 Prepared By : _____
 Checked By : _____

EMERGENCY LIGHT



ORDERING INFORMATION

Product Code	Voltage	Discharge Time	Remote	Self Diagnostic
KL-7090	120/277V	90 Minutes	/	/
KL-7090-RC*	120/277V	90 Minutes	5W	/
KL-7090-AT*	120/277V	90 Minutes	/	YES
KL-7090-220*	220-240V	180 Minutes	/	/

*Not In Stock

FEATURES

- LED Technology
- High Visibility
- Multiple Mounting Options
- Battery Backup for power cut situations
- Photoluminescent Signs that glow in Dark
- Follow Compliance and Regulations- UL Listed

SPECIFICATIONS

Operating Temperature	-10°C - +45°C
Product Wattage	4.8W
Input Voltage Range	120-277 VAC
Input Frequency	60Hz
Power Factor	1
Battery	3.6V NiCad - Maintenance Free
Charging Time	24 Hours
Discharge Time	90 Minutes
Mounting	Wall & Ceiling
Finish	White
Frame Material	ABS
Ingress Protection	IP20
Impact Protection	03

Our Standard LED Emergency Lights, colloquially known as "Bug Eye" lights, are versatile fixtures suitable for both indoor and outdoor applications. Mimicking the appearance of bug eyes, these units feature a dual LED light head design housed in a robust plastic casing. Engineered for durability and longevity, the housing contains high-quality LED lights and accessories, making it a reliable choice for various emergency lighting needs.



Warranty



Rated Life



(864) 401-8156
 sales@krutled.com

111 Preamble Ct, Anderson, SC- 29621, United States.

All rights reserved. Krut LED reserves the right to make changes to specifications and/or discontinue any product at anytime without the notice. Information presented in this document is reliable and accurate, It does not represent any quotation or contact. No liability will be accepted by the contributor by the publisher for any consequences for its use. Reproduction in whole or part is prohibited without prior consent of the copyright owner.




Article No :
 Version : 08.25
 Prepared By :
 Checked By :

OPTICAL PARAMETERS

Total Lumens (Min)	320lm
Product Efficacy (Min)	77.86 lm/W
Product CCT	6500K
CCT Range	5500-7500K
Product CRI	> 80 Ra
Product Beam Angle	27.3 DEG

DIMENSION



SHIPPING

Product Dimension (in)	Case Lot	Master Carton Dim. (in)	40' HQ Container Qty	Pallet Qty
12.37 x 4.46 x 3.60	10	13.27 x 10.31 x 16.10	1960 Nos	190 Nos

(864) 401-8156
 sales@krutled.com
 111 Preamble Ct, Anderson, SC- 29621, United States.

All rights reserved. Krut LED reserves the right to make changes to specifications and/or discontinue any product at anytime without the notice.
 Information presented in this document is reliable and accurate, It does not represent any quotation or contact.
 No liability will be accepted by the contributor by the publisher for any consequences for its use.
 Reproduction in whole or part is prohibited without prior consent of the copyright owner.




Article No	:	
Version	:	08.25
Prepared By	:	
Checked By	:	

INSTALLATION INSTRUCTIONS



NOTE: First turn off electricity.

Wall mounting (Max. mounting height: 19.6ft)

1. Remove mounting plate from fixture.



2. Knockout in back of mounting plate and push wires through the hole.
3. Securely attach mounting plate to J-box. Max. mounting height is 8.30ft.




4. ELECTRICAL CONNECTIONS


Make the proper supply wire connections.

If using 120VAC, connect the black and White wires to the building utility.

If using 277 VAC, connect the Orange and White wires to the building utility.




5. Connect the battery to connector on the PCBA.



6. Snap fixture onto mounting plate and ensure no wires are pinched. Make sure unit is fully attached.
7. Restore power and press test button. Battery powered LED will come on, AC light will turn off.

Ceiling Mounting

1. Open top cover and knockout on the top of fixture.
2. Secure the mounting plate to tube with nut.



3. Reference step 4 - 7 in wall mounting above for ceiling mounting.