HAVELLS

SWITCHABLE
EMERGENCY EXIT SIGN

Catalog#	
Project:	
Fixture Type:	Date:
Note:	

Hit the Tab key or mouse over the page to see all interactive elements.

The Switchable Emergency Exit Sign is an essential safety fixture that provides reliable illumination during emergencies and power outages. It clearly marks exit routes, enabling safe, quick evacuation while enhancing overall building safety.



FEATURES & BENEFITS

- Innovative, easy installation in minutes
- Interchangeable Red or Green Lettering
- 90 minutes Emergency Operation
- Maintenance-Free NiCad Battery
- Durable 5VA-Rated Flame-Retardant Thermoplastic Housing
- Top, End, or Back Wall/Ceiling Mounting
- Supports Single or Double-Face Mounting
- UL 924 Certified for Emergency Lighting

UL LISTED | DAMP LOCATION | INBUILT EMERGENCY BATTERY BACKUP | CHANGEABLE LETTERS

Model Number	Input Current	Wattage	LED Type	Charging Time	Emergency Run Time
HL-EX-E	0.02A	1.1W	6 Red LEDs + 6 Green LEDs	24 hours	90 Minutes

PRODUCT SUMMARY

Input Voltage
120–277 Vac

Battery Type
Nickel Cadmium (1.2V)

Finish
White

Operating Temp.
32°F to +104°F

Input Current
0.02A

Mounting
Wall, Ceiling & Side

Discharge Time
90-Minutes


Dimming
No

Housing Material
Thermoplastic ABS

Recharge Time
24 hours

Warranty
5 Years

DIMENSIONS



Length (L)
11.61 Inch

Width (W)
7.17 Inch

Height (H)
1.81 Inch

APPLICATIONS

- Commercial Buildings & Offices, Industrial Facilities, Large Public Venues, Hospitality & Healthcare and Retail Centers & Malls.

INCLUDED ACCESSORIES

- Mounting Hardware & Wiring Kit, Diffuser and Battery.

PACKAGING DETAILS

Model No.	Product Dimension (LxWxH) (in)	Case Qty (units)	Case Dimension (LxWxH) (in)	Net Weight Product (lbs)	Gross Weight with Packaging (lbs)	Pallet Load
HL-EX-E	11.61 x 7.17 x 1.81	6	15.16 x 12.4 x 8.46	1.5	2.1	-

www.havellsLighting.com salesusa@havells.com 855-428-3557
© Havells Lighting LLC | All Rights Reserved.
Specifications and Data Subject to change without Notice.